



By selecting the combination on the DIP switch, sensor data can be precisely set for each specific application.

### 1. Detection area

Detection area can be reduced by selecting the combination on the DIP switches to fit precisely each application.

#### ● Factory Default

ON ↑ [DIP Switch]		1	
	I	ON	100%
	II	-	50%

### 2. Hold time

Refers to the time period the lamp remains at 100% illumination after no motion detected.

ON ↑ [DIP Switch]		2	3	4	
	I	ON	ON	ON	5s
	II	-	ON	ON	30s
	III	ON	-	ON	90s
	IV	-	-	ON	3min
	V	ON	ON	-	20min
	VI	-	-	-	30min

### 3. Stand-by period

Refers to the time period the lamp remains at a low light level before it completely switches off in the long absence of people. When set to  $+\infty$  the low light is maintained until motion is detected.

ON ↑ [DIP Switch]		5	6	7	
	I	ON	ON	ON	$+\infty$
	II	-	ON	ON	60min
	III	ON	-	ON	30min
	IV	-	-	ON	10min
	V	ON	ON	-	5min
	VI	-	-	-	5s

### 4. Stand-by dimming level

The low light level you would like to have after the hold time in the long absence of people.

ON ↑ [DIP Switch]		8	9	
	I	ON	ON	50%
	II	-	ON	30%
	III	ON	-	20%
	IV	-	-	10%

### 5. Daylight sensor

The sensor can be set to only allow the lamp to illuminate below a defined ambient brightness threshold.

When set to Disable mode, the daylight sensor will switch on the lamp when motion is detected regardless of ambient light level.

Note that daylight sensor is active only when lamp totally switches off.

ON ↑ [DIP Switch]		10	11	12	
	I	ON	ON	ON	Disable
	II	-	ON	-	200lux
	III	ON	-	-	100lux
	IV	-	-	-	50lux


#### ● Factory Default



Max.8M



Hold Time  
10s~30min



Mounting Height  
15 m Max.



Automatic  
Dimming

